

Total No. of Questions : 10 ] [ Total No. of Printed Pages : 5

Roll No. ....

## CS/EC/IT-401(NGS)

B. E. (Fourth Semester) EXAMINATION, June, 2012

(Non-Grading System)

(Common For CS, EC & IT Engg. Branch)

COMPUTER SYSTEM ORGANIZATION

*Time : Three Hours*

*Maximum Marks : 100*

*Minimum Pass Marks : 35*

**Note :** The question paper is divided into five Units. Each Unit carries an internal choice. Attempt *one* question from each Unit. Thus attempt *five* questions in all. All questions carry equal marks. Assume suitable data whenever necessary.

### Unit - I

1. (i) A two-word instruction is stored in memory at an address designated by symbol  $w$ . The address field of the instruction (stored at  $w + 1$ ) is designated by symbol  $y$ . The operand used during the execution of instruction is stored at an address symbolized by  $z$ . An index register contains the value  $x$ . State how  $z$  is calculated from other address if the addressing mode of instruction is :

(a) - Direct

P. T. O.

- (b) Indirect
  - (c) Relative
  - (d) Indexed
- (ii) Write a program to evaluate the arithmetic statement : 10

$$X = \frac{A - B + C * (D + E - F)}{G + H * K}$$

- (a) Using a general register computer with three address instructions. 6
  - (b) Using a general register computer with two address instructions. 4
  - (c) Using a accumulator type computer with one address instructions. 10
  - (d) Using a stack organized computer with zero address operation instructions.
2. (i) Draw the functional and structural views of a computer system and explain in detail. 6
- (ii) What are the major steps a processor has to perform to execute an instruction ? Explain briefly. 4
- (iii) Explain the internal architecture of 8085 with a neat block diagram. 10

#### Unit - II

3. (i) With the help of a neat diagram and example, explain the working of a typical microprogrammed control unit. 10
- (ii) What is meant by Normalization ? Explain the IEEE standards to represent floating point number. 5
- (iii) Draw and explain the block diagram of general purpose register architecture of CPU. 5

Or

4. (i) A digital computer has a common bus system for 16 registers of 32 bits each. The bus is constructed with multiplexers : 6
- (a) How many selection inputs are there in each multiplexer ?
- (b) How many multiplexers are there in the bus ?
- (ii) Explain Booth's multiplication algorithm through an example. Give an example of multiplication and multiplier for which this algorithm takes the maximum time. 10
- (iii) Compare horizontal microcode with vertical microcode. State the advantage of microprogrammed control unit. 4

Unit - III

5. (i) Explain the interrupt process in 8085 and the difference between a non-maskable and a maskable interrupt. 10
- (ii) Describe the function of DMA controller in data transfer between I/O and memory. State different modes of DMA operation. 6
- (iii) State the difference between I/O mapped I/O and memory mapped I/O. 4

Or

6. (i) Define the following : 10
- (a) Asynchronous Data Transfer
- (b) Asynchronous Communication Interface

P. T. O.

- (ii) What is Interrupt ? Describe different types of interrupts and their use. How a processor handles a vectored interrupt ? 10

Unit – IV

7. (i) Explain a typical associative memory organization. Describe the various steps involved in accessing the content of the associative memory. 10
- (ii) A memory system contains a cache, a main memory and a virtual memory. The access time of cache memory is 5 nsec and it has 80% hit rate. The access time of main memory is 100 nsec and it has 99.5% hit rate. The access time of virtual memory is 10 msec. What is the average access time of the hierarchy ? 5
- (iii) Give a block diagram for 512 K \* 32 memory using 64 K \* 8 memory chips and explain. 5

Or

8. (i) Discuss the different mapping techniques used for cache memory. What is the need of mapping techniques ? 10
- (ii) For a set associative cache organization, the parameters are as follows : 10

$T_c$  → Cache access time

$T_m$  → Memory access time

L → Number of sets

B → Block size

K \* B → Set size

Calculate hit ratio for loop executed 100 times where the size of loop is N \* B and N = K \* M is a non-negative integer and  $1 < M \leq L$ .

[ 5 ]

Unit - V

9. (i) What are Pipeline Hazards ? What are the causes of pipeline hazards ? Describe briefly the hazard detection and resolution of hazards in pipelines. 10
- (ii) A program repeatedly executes a loop that has 120 iterations. Each iteration takes 10000 cycles. On multiprocessor systems, 50000 cycles are required to synchronize the processor once all iteration of loop have completed : 10
- (a) What is the execution time of each loop on a uniprocessor system ?
- (b) What is the execution time of each loop on a 2-processor system, and what is the speedup over the uniprocessor system ?
- (c) What is the execution time of each loop on a 4-processor system and what is the speedup over the uniprocessor system ?

Or

10. Write short notes on the following : 20
- (i) Multiprocessor systems
- (ii) Message passing system
- (iii) Shared memory system
- (iv) Interprocess communication